brother At your side.

HL-2070N
Network Ready Laser Printer

Brother | HL-2070N

HL-2070N
Network Ready
20 page per minute
Personal Laser Printer

- up to 20 ppm — Up to 20ppm Print Speed
- NETWORK — Network Ready
- Designed for Microsoft® Windows® — Windows™ Compatible
- Mac — Mac™ Compatible
- Linux™ Compatible
- USB2.0 / Parallel
- up to 250 pages — Paper Capacity Up to 250 pages
- HELP — 24 hour 7 day Online Help
- OPTIONAL — Optional Wireless Network

HL-2070N

Technical Specification

ENGINE		
Technology		Electrophotographic
Print Speed	A4	Up to 20 ppm
First Print Time		Less than 10 sec
Resolution	Windows® 95 / 98 /Me NT4.0 /2000 / XP	HQ1200 (2400 x 600) / 600 / 300dpi
	Mac OS® 9.1-9.2, OSX® 10.2.4 or greater	HQ1200 (2,400 x 600) / 600 / 300dpi
	Linux	600 / 300 dpi
CONTROLLER		
Processor		SPARClite 133MHz
Memory		16MB
Interface	Standard	Full-Speed USB2.0, IEEE 1284 Parallel 10/100 BaseTX Ethernet as standard
Network Connectivity	Wired	Standard 10/100 BaseTX Ethernet
	Protocol	TCP/IP: ARP, RARP, BOOTP, DHCP, WINS/NetBIOS, LPR/LPD, Port9100, POP3/SMTP, SMB Print, TELNET, SNMP, HTTP, TFTP, NetBEUI
	Wireless (Optional)	NC-2200w (USB) 802.11b
	Protocol	TCP/IP ARP,RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS, DNS, LPR/LPD, Raw Port/Port9100, SMB Print, IPP, FTP, mDNS, TELNET, SNMP, HTTP
Management Tool	BRAdmin Professional	Brother original Windows utility for print server management
	Web BRAdmin	Download from http://solutions.brother.com
	Web Based Management	Print and print server management through Web browser
Emulation		PCL®6, IBM®Proprinter XL, Epson® FX-850
Resident Fonts	PCL	49 scalable fonts, 12 bitmap fonts, 11 bar codes
SOFTWARE		
Printer Driver	For Windows®	PCL Driver for Windows® 95 / 98 / Me and NT®4.0/2000 / XP
	For Macintosh®	Brother Laser Driver for Mac® 9.1-9.2, MacOS® X 10.2.4 or greater
	For Linux	GDI Driver for Linux (Download from http://solutions.brother.com)
Utilities	Interactive Help	Instructional movie to provide a solution when any error message appears on the Status Monitor
CONTROL PANEL		
Display	LED	4 LED (Toner/Drum/Paper/Ready)
Buttons	1 button	Go
PAPER HANDLING		
Paper Input	Manual Feed Slot	1 Sheet
	Paper Tray	Up to 250 Sheets^ can be stored in paper tray
Paper Output	Face Down	Up to 100 Sheets^ can be stored in the output tray face down
Duplex	Manual Duplex	Yes

MEDIA SPECIFICATIONS			
Media Types	Manual Feed Slot	Plain Paper, Bond Paper, Recycled Paper, Envelopes, Labels, and Transparencies	
	Paper Tray	Plain Paper, Bond Paper, Recycled Paper, Transparencies (up to 10 sheets^)	
Media Weights	Manual Feed Slot	60 - 161 gsm	
	Paper Tray	60 - 105 gsm	
Media Sizes	Manual Feed Slot	Width 69.9 to 215.9 mm, Length 116 to 406.4 mm	
	Paper Tray	A4, Letter, B5(JIS), B5(ISO), A5, B6, A6, Exe	
PRINTER DRIVER FUNCTIONS			
Page Layout	N in 1 Printing	Condense 2, 4, 9, 16 or 25 pages into 1 page	
	Poster Printing	Enlarge 1 page to print over 4, 9, 16 or 25 pages	
	Watermark Printing	Watermark documents with predefined text or user defined messages	
Others	Quick Print Setup	A printer driver function that enables you to change the driver setting without opening property dialog.	
	Status Monitor	A function to indicate the printer error on the PC	
SUPPLIES			
Toner	TN-2025	Up to 2,500 A4 pages @ 5% coverage	
Drum	DR-2025	Up to 12,000 A4 pages (1 page / job)	
DIMENSION/WEIGHT			
Dimensions (W x D x H)		371 x 361 x 165.5 mm	
Weight		6.5kg	
OTHERS			
Power Consumption	Printing	Less than 450W	
	Standby	Less than 70W	
	Sleep	Less than 7W	
Noise Level	Sound Pressure	Printing	51dB(A) or less
		Standby	30dB(A) or less
	Sound Power	Printing	6.2B(A) or less
		Standby	4.3B(A) or less
Ecology	Power Saving	Yes	
	Toner Saving	Yes	
OPTIONS			
Network Interface	Wireless Print Server	Optional External Print Server (NC-2200w) 802.11b (USB Host)	

use only GENUINE brother supplies

Brother strongly recommends that our customers use Genuine Brother consumable products only. By using genuine Brother consumables the benefits to you are:

- Better quality prints
- Greater yields per consumable
- You protect your machine from damages
- Achieve optimum performance.

Your machine warranty may not cover any damages arising from the use of non-genuine Brother® consumables.
Your machine should be used only in a clean, dust-free environment

HL-2070N	Operating System Version	Processor Speed	Minimum RAM	Recommended RAM	Available Hard Disk Space
Windows	95, 98, 98SE	486-66MHz	8MB	16MB	40MB
	NT® 4.0	Pentium 75MHz	16MB	32MB	50MB
	2000 Professional	Pentium 133MHz	64MB	128MB	50MB
	Me	Pentium 150MHz	32MB	64MB	50MB
	XP	Pentium 300MHZ	128MB	128MB	50MB
Macintosh	OS 9.1- 9.2	All base models meet	32MB	64MB	50MB
	OSX 10.2.4 or greater	minimum requirements	128MB	160MB	50MB

User Friendly Front Loading Consumables

^at 75gsm A4 paper

Contact:

At your side.

Brother International (Aust) Pty Ltd

Web-site: www.brother.com.au Technical Help Web-site:http://solutions.brother.com
NSW/ACT 7 Khartoum Rd. North Ryde NSW 2113 Phone: (02) 9887 4344 Fax: (02) 9870 7234
VIC 43 Carrington Rd. Box Hill VIC 3128 Phone: (03) 9899 4844 Fax: (03) 9899 4833
QLD/NT 245 Riverside Drive. West End QLD 4101 Phone: (07) 3255 1211 Fax: (07) 3255 1911
SA/TAS Unit 4, 13 King William Rd. Unley SA 5061 Phone: (08) 8272 1300 Fax: (08) 8272 1199
WA 117 Great Eastern Highway. Belmont WA 6104 Phone: (08) 9478 1955 Fax: (08) 9277 2177

All specifications subject to change without notice